

Wire Trackers

- No Calibration is needed for general measurement;
 - Allow User Calibration for precise measurement;
 - Able to measure cable made of different material;
 - Only need to connect the cable at one side;
 - Measure up to 600 meters;
 - Able to measure LAN cable (both 4P4C & 8P8C), Phone wire and BNC cable;
 - Intelligent wiremap Shorts, Split Pairs, and Breakpoint Checking);
 - Tracing cables connected to ethernet hub with PoE support;
 - Have Remote Identification Function (Optional);
 - Auto power off;
 - With display backlight and flashlight;
 - Sensitivity adjustable;
 - With Built-in Multimeter Functions.





Specifications

| | | WISED | WISE |
|--|---------------|-----------------------------------|-----------|
| Cable Length Measurement | | | |
| 2-400m | Resolution | 0.1m | |
| | Best Accuracy | ±(1%+5) | |
| 2-600m | Resolution | | 0.1m |
| | Best Accuracy | | ±(1%+5) |
| Intelligent Wiremap | | | |
| Shorts | | ✓ | ✓ |
| Split pair | | ✓ | ✓ |
| Breakpoint checking | | ✓ | ✓ |
| Length of Network Cable | (8P8C) | ✓ | ✓ |
| Length of Network Cable | (4P4C) | ✓ | ✓ |
| Length of Phone Cable | | ✓ | ✓ |
| Length of BNC Cable | | ✓ | ✓ |
| Analogue Cable Tracing | | ✓ | ✓ |
| Digitalized Cable Tracing | | | ✓ |
| Port Blink Test | | ✓ | ✓ |
| Voltage Measurement (via network cable jack for reference) | | ✓ | ✓ |
| PoE Voltage Polarity Checking | | ✓ | ✓ |
| POE Voltage measurement (for reference only) | | ✓ | ✓ |
| Continuity (via network cable jack) | | ✓ | ✓ |
| PoE Voltage Protection | | ✓ | ✓ |
| Vibration inducation | | | ✓ |
| Remote Identification (Optional) | | 7 | 7 |
| User Calibratable | | ✓ | ✓ |
| User Calibration Result Storage | | ✓ | ✓ |
| Multimeter | | | |
| DC Voltage | 400mV-600V | ±(0.8%+3) | ±(0.8%+3) |
| AC Voltage | 4V-400V | ±(1.5%+5) | ±(1.5%+5) |
| DC Current | 1A-10A | ±(1.2%+4) | ±(1.2%+4) |
| AC Current | 1A-10A | ±(2%+5) | ±(2%+5) |
| Resistance | 200Ω-20ΜΩ | ±(2%+6) | ±(2%+6) |
| Diode | | √ | √ |
| Continuity | | ✓ | ✓ |
| Temperature | | ±(2%+15) | ±(2%+15) |
| Max Display | | 9999 | 9999 |
| Display Backlight | | ✓ | ✓ |
| Flashlight | | √ | ✓ |
| Sensitivity adjustable | | · ✓ | ✓ |
| Low power indication | | · ✓ | ✓ |
| Auto power off | | · | · |
| Power By | Main Body: | 3.7V, 1250mAH Lithium Ion Battery | |
| Tower By | Receiver: | 9V (6F22) | |
| | TOOGRAFIE | 0 V (OI ZZ) | |

* All information provided are subject to change without prior notice.



HONG KONG www.futronix-hk.com info@futronix-hk.com





Your Distributor: