

# Value+

## Non-contact Voltage Detectors (w/ bargraph indication)

- 5 segments bargraph indicator(s) for easy interpretation
- With audio indication
- Measuring from 90V to 1000V (CAT IV), suitable for a wide range of residential, commercial and industrial needs
- Built-in white torch at the front end for helping to search the testing point in dark
- Integrated clip design, optimized for pocket storage
- Auto Power Off to enhance the battery life
- Safe and Easy to use



# Non-contact Voltage Detectors (w/ bargraph indication)



	NF13A	NF13B
AC Voltage	90-1000V	90-1000V
Frequency	40-400Hz	40-400Hz
Indicated by		
LED Flashing (5 Segments)	✓	
LCD Indicating (5 Segments)		✓
Beep Sound (Switchable)	✓	✓
On / Off Button	✓	✓
Switch on Indication	✓	✓
Standby Indication	✓	✓
Flashlight	✓	✓
Low Battery Indicator	✓	✓
Auto Power Off	✓	✓
Overload Protection	CAT IV 1000V	
Power by	1.5V (AAA) x 2	

\* All information provided are subject to change without prior notice.



Your Distributor :



**Futronix Co.**  
HONG KONG  
www.futronix-hk.com  
info@futronix-hk.com